

# Flexbus 220 mm<sup>2</sup>, 22 000 mm x 25 mm x 12.5 mm x 28.3 kg

## Data Solutions

???

### FLEXCOND220L22



nVent ERIFLEX Flexbus  
 ???  
 ??????????????????????Flexbus Advanced  
 ???Flex  
 bus?????????????????LSHFRR??????II?????????Flexbus????????????  
 ??????????????????2-25????????????????????500A-  
 6300A?????????1600KVA????????????????????????????????????3150KVA  
 ????????????????????

??



??

??????????????????
????????????????????
???????
?????????
????????????????????
?????400KVA?560A??1600KVA(2250A)?,????????????2000kVA (2800 A) ? 3150kVA (4435 A)?????????????

????

???: 508221
???: 220mm <sup>2</sup>

?? 1 (L1): 22000mm

?? 2 (L2): 50mm

????: ???

?????: ??

?????: ?

?????: 500% min

?????: 2.5 – 3.5mm

?????: 20kV/mm

?????: UL® 94V-0

?????: UL® 2885; IEC® 60754-1; IEC® 62821-2

?????: IEC® 61034-2; ISO 5659-2; UL® 2885

?????: IK09

?????: UL® 2556; UL® 854

????: 0.2mm

?????IEC: 1000V; 1500V

???????EN 50264-3-1: 6000V

????: ?50 to 115°C

?: IEC® 60695-2-11??????? 960 °C?; IEC® 61439.1; IEC® 61439.1 II ?; IEC® 60364

?T 60 K: 666A

?? 1 (W1): 58mm

?? 2 (W2): 50mm

?? [1] (H1): 16.2mm

?? [2] (H2): 9mm

??? (HS): 11mm

????: 28.3kg

A: 25mm

C: 25mm

D: 12.5mm

2 ??????????: 1.56

2 ??????????: 2

????: AS 3008; BS 7671; CEI 64-8; CSN; DIN VDE 0100; HD 384; IEC® 60364; NBR 5410; NEN 1010; NFC 15-100; NIBT-NIN; NP (2002); ÔNORM; REBT; RGIE-AREI

??????

????????????????

??	?T 30°C	?T 40°C	?T 45°C	?T 50°C	?T 55°C	?T 60°C	?T 65°C	?T 70°C
????	0.71	0.82	0.87	0.91	0.96	1.00	1.04	1.08



??? nVent ?????????????????? nVent ??????? www.nvent.com ?????????????? nVent ?? nVent  
 ???



?????????????:  
 CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE