

□□□□□□ , 80 A IEC, 85 A UL/CSA, □□
Line, 6 □□□□ Load, □□ , □□□□□□

Data Solutions

???

UD-80A



??



??

????????????????????????????

????????????

????????????????

????????????????

????? DIN ?????????

??? 95%

????????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

???

????????

????

???: 569010



??: ??
???????IEC: 80A
???????UL/CSA: 85A
?????: ??
?????: 6 ???
?: ?; ???
?????????IEC: 16 mm ²
?????????IEC: 16 mm ²
???????IEC (Ui): 1000
???????UL (Vin): 600
????? (ICW) 1 ?: 3kA
????? (Ipk): 22kA
???????? (ICC): 11kA
????? (SCCR): 100kA
????????: 1
?????????: 6-16 mm ²
????????: 16 min
????????: 6
?????????: (2) 2,5 - 16 mm ² ; (4) 2,5 - 6 mm ²
???????? - ?: (2) 2,5 - 16 mm ² ; (4) 2,5 - 6 mm ²
????????: (2) #16 - #4; (4) #16 - #8
?????: IP 20
?? (D): 46mm
?? (H): 69mm
?? (W): 30mm
????: 0.07kg
?????: UL® 1059
?????: UL® 94V-0
?: IEC® 60947-7-1

??????

????????????160A?IEC????????????

UL ?????????1000V AC/DC????????

????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*????????										



???? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????? nVent
??



?????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE