

PDU EB0328 230 VAC 1-PH 32 A

Data Solutions

???

EB0328



Modular, compact PDU. Ultra-Low Profile Design

??

Enlogic ?????????????????????????????????

???? 230 VAC, 1 ?

C13 ? C19 ??

1RU ????

??????????

????

????: Enlogic

?: ??? PDU

????: ??

????: (24) C13; (6) C19

????: 30

?: ??

?: 16 A?1 ??Hy-Mag

????: ?

?????: 2

????: 7.4 kVA
?????: ????

????: 200 – 240V
?: 1 ?

?????: 5kAIC
?????: 7.44 kVA

????: 230V
???/???: ?

????: 230VAC
?????: 32 A

????: IEC 60309 332P6 (IP44)
????: 0U

?????: ?
????: ?

?: ?
?: ????

?: 1490mm
?: 52mm

?: 53mm
?: 9.5kg

????: 1
?????: 3m

??????

????????????

??

???? nVent ????????????????? nVent ??????? www.nvent.com ??????????? nVent ????????????????????????????????????? nVent
??/????????????



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE